

## How to Update the KROME Operating System

*Important: Back up your sounds and settings before doing any OS update. Use the "Save PCG" (Programs, Combinations, Global data) or "Save All" commands, which are located in the Media mode. Please refer to page 118 of the KROME Operation Guide for detailed instructions.*

This download contains a folder named "KROME". Please copy the extracted folder from your computer onto the root of an MS-DOS-formatted SD card, and follow the procedure below.

### Installing the new Operating System:

- 1) Turn the KROME's power ON.
- 2) Insert the SD card containing the "KROME" folder, as described above.
- 3) Press the GLOBAL button to enter Global mode, then touch the drop-down menu and select the command "Update System Software". The system will begin updating automatically.

**DO NOT TURN OFF THE POWER WHILE THE SYSTEM IS UPDATING.**

- 4) When the update is finished, the display will read "Completed". Please turn the power off, and then on again.

*Note: If a "File/path not found" message is displayed after selecting "Update System Software" in step #3, please ensure that the "KROME" folder is copied correctly on the root of the SD card, and repeat the steps.*

*Note: If the error message "Error in reading from medium" or "Can't update system" appears, please delete the "KROME" folder from the SD card, copy the "KROME" folder from the computer to the SD card again, and repeat step #3. If the error persists, please try reformatting the SD card or try a different SD card.*

Korg has also improved many of the factory Programs and Combinations since version 1.0.0. If you are updating directly from version 1.0.0 to version 1.0.4, please follow the instructions under "Updating the Programs and Combinations" after installing the new software.

*Note: The updates for versions 1.0.1, 1.0.2 and 1.0.3 also included these improved sounds. It is only necessary to update the Programs and Combinations when installing version 1.0.4 directly over the original version 1.0.0.*

**IMPORTANT:** Be sure to back up your customized sounds and settings before following these steps, which will overwrite Programs, Combinations, Drum Kits, Arpeggio Patterns and Global data. Please refer to page 118 of the KROME Operation Guide for detailed instructions.

### Updating the Programs and Combinations:

- 1) Press the GLOBAL button to enter Global mode.
- 2) Open the drop-down menu, and select "Load Preload/Demo Data".
- 3) Select "All Preload Data" and press "OK".